
Appendix A – WDT1730

[REDACTED]
[REDACTED]

Queue Cluster 14 Phase II Report

January 30, 2024

This study has been completed in coordination with the California Independent System Operator Corporation (ISO) per Southern California Edison Company's Wholesale Distribution Access Tariff (WDAT), Attachment I Generator Interconnection Procedures (GIP)

This document may include confidential trade secrets, Critical Energy Infrastructure Information (CEII), and proprietary information of Southern California Edison (SCE) to be used by [REDACTED], in connection with its evaluation of this QC14 Phase II Study. SCE retains all rights to maintain the confidentiality of this information and requires that [REDACTED] preserve its confidentiality."

TABLE OF CONTENTS

A. Introduction	1
B. Report Objective.....	1
C. Description of Generating Facility.....	2
D. Study Assumptions	6
E. Study Results	10
F. Affected Systems	17
G. Deliverability Assessment Results.....	18
H. Metering	19
I. Interconnection Facilities, Network Upgrades, and Distribution Upgrades	19
J. Cost and Duration Estimate.....	19
K. In-Service Date and Commercial Operation Date Assessment.....	22
L. TIMING OF FULL CAPACITY DELIVERABILITY STATUS, INTERIM DELIVERABILITY STATUS, AREA CONSTRAINTS, AND OPERATIONAL INFORMATION.....	24
Attachment 1: Interconnection Facilities, Network Upgrades, and Distribution Upgrades.....	25
Attachment 2: Escalated Cost and Time to Construct for Interconnection Facilities, Reliability Network Upgrades, Delivery Network Upgrades, and Distribution Upgrades	26
Attachment 3: Allocation of Network Upgrades for Cost Estimates and Maximum Network Upgrade Cost Responsibility	27
Attachment 4: SCE’s Interconnection Handbook.....	28
Attachment 5: Short-Circuit Duty Calculation Study Results	29
Attachment 6: IC Provided Generating Facility Dynamic Data	30
Attachment 7: Subtransmission Assessment Report (SAR)	31

A. INTRODUCTION

[REDACTED], the Interconnection Customer (“IC”), has submitted a completed Interconnection Request (“IR”) to Southern California Edison (“SCE”), the Distribution Provider, for its proposed [REDACTED] (“Generating Facility”). The IC’s IR requested [REDACTED] [REDACTED] for the Generating Facility. The proposed Generating Facility includes a [REDACTED] [REDACTED] and the IC has requested [REDACTED]. The IC’s IR and/or Attachment B stipulated the IC requested [REDACTED] [REDACTED] [REDACTED], respectively. However, the ISD and

COD for the Generating Facility will depend on the estimated duration required for licensing, engineering, detailed design, procurement, and construction requirements to interconnect the Generating Facility. The estimated duration for these activities would commence after the Generator Interconnection Agreement (“GIA”) for the Generating Facility has been executed and/or filed at the Federal Energy Regulatory Commission (“FERC”) for acceptance and funded.

In accordance with FERC’s approved SCE’s Wholesale Distribution Access Tariff (“WDAT”) Attachment I Generator Interconnection Procedures (“GIP”), the Generating Facility was grouped with Queue Cluster 14 (“QC14”) Phase II projects to determine the impacts of the group as well as impacts of the Generating Facility on SCE’s Distribution System and the ISO Grid. An Area Report and, where applicable, a Subtransmission Assessment Report (“SAR”) have been prepared separately to discuss the combined impacts of all projects on the ISO Grid and to the distribution facilities served out of the [REDACTED] Subtransmission System, respectively. This Appendix A report focuses only on the impacts or impact contributions of the Generating Facility to SCE’s Electric System and is not intended to supersede any contractual terms or conditions specified in a forthcoming GIA.

B. REPORT OBJECTIVE

SCE performed a QC14 Phase II Study that included the Generating Facility, and this report addresses the results of the analysis.

The report provides the following:

1. Transmission and Non-ISO controlled Subtransmission System impacts attributed to the proposed Generating Facility.
2. System reinforcements or mitigation necessary to address the adverse impacts attributed to the Generating Facility under various system conditions.
3. A list of required facilities and a good faith estimate of the IC’s cost responsibility for its proposed Generating Facility and SCE’s project execution schedule². Such information is provided in Attachment 1 and Attachment 2 as separate documents in the Appendix A report package for the Generating Facility. Specifically, the facilities that will be installed by SCE and the IC are detailed in Attachment 1.

¹ Refer to GIP Section 4.6.13

² It should be noted that construction is only part of the estimated duration of months specified in the study, which includes final engineering, licensing, and other activities required to bring such facilities into service. These durations are from the execution of the GIA, receipt of: all required information, funding, and written authorization to proceed with design and engineering, procurement, and construction from the IC as will be specified in the GIA to commence the work.

4. Identification of potential short circuit duty impacts to Affected Systems served from the Transmission, Subtransmission or Distribution System.

The Generating Facility [REDACTED], as a result an As-Available Charging Distribution Service (“ACDS”) analysis to determine the charging impacts on SCE’s Electric System was conducted as well. The analyses focused on the Charging Capacity³ aspects of the Generating Facility and considered varying levels of system demand with minimal generation dispatch within the local distribution system.


Accordingly, this report also discloses the following:

- a. The adequacy of SCE’s Electric System to support the Generating Facility under ACDS.
- b. Provides a high-level explanation of the potential exposure to the Generating Facility of charging restrictions on the electric system.
- c. The service level, which is based on the Point of Interconnection (“POI”) of the Generating Facility, enables the IC to determine the applicable As-Available Energy Charge Rate (\$/kWh).


C. DESCRIPTION OF GENERATING FACILITY

Generating Facility: all equipment and facilities comprising the IC’s [REDACTED]
Generating Facility with a [REDACTED]
[REDACTED]
[REDACTED]
[REDACTED] as disclosed by the IC in its IR and/or Attachment B, as may have been amended during the Interconnection Study process. The facilities are, summarized below:

Table C.1: Generating Facility General Information per the IR and/or Attachment B



³ Charging Capacity: The load associated with the storage component of a Generating Facility charged from the Distribution System that is used for later redelivery of the associated energy, net of Resource losses, to the Distribution System. Charging Capacity does not include load that is subject to SCE’s retail tariff.



Note: Detailed loss analysis used in defining net capability at high side of main transformer bank and net capacity at the POI.

In addition, the IC will install [REDACTED]
[REDACTED]
[REDACTED].

Generation Export Limit for the Generating Facility

The IC has requested a [REDACTED] SCE and the IC acknowledge that since the Generating Facility is capable of exceeding these values the IC agrees to: install, own, operate and maintain a control limiting device or, alternatively, by means of configuring the Generating Facility’s control system. This is to ensure the Generating Facility does not exceed the total net capacity at the high-side of the main step-up transformer(s) and at the POI.

Charging Capacity Limit for the Generating Facility

[REDACTED]. The Parties acknowledge that since these values can be exceeded, the IC agrees to install, own, operate and maintain a control limiting device or, alternatively, by means of configuring the Generating Facility’s control system. This is to ensure the Generating Facility does not exceed these total Charging Capacity values at the high-side of the main step-up transformer(s) and at the POI.

The scope of facilities, required to interconnect the proposed Generating Facility and provide the [REDACTED] and in support of the Charging Capacity for ACDS, are detailed in Attachment 1 to this Appendix A report. The proposed plan for interconnecting the Generating Facility is illustrated in Figure C.1. and Figure C.2 illustrates the proposed location of the Generating Facility. Additional information is provided in Table C.2

Figure C.1: Generating Facility One-Line Diagram




Figure C.2: Generating Facility Location Map




Table C.2: Additional Generating Facility General Information per IR and/or Attachment B

Generating Facility Location	
SCE's Planning Area	
Interconnection Voltage	
POI	
High Fire Risk Area	
Requested Maximum Generating Facility Delivery at Point of Interconnection ⁵	
Number and Types of Generators	
Generation Tie Line	
Main Step-Up Transformer(s) Main Transformers T	
Collector Equivalent	
Pad-Mount Transformer(s) Downstream of Main Transformer Bank T	
Generator Data Downstream of Main Transformer Bank T	
Generator Auxiliary Load and/or Station Light and Power	
Voltage Regulation Devices Downstream of Main Transformer Bank T	
Dynamic Models Used	

The Generating Facility was modeled as described in Table C.1 and C.2 above.

D. STUDY ASSUMPTIONS


For detailed assumptions regarding the evaluation on the SCE Transmission and Non-ISO controlled Subtransmission System, please refer to the QC14 Phase II Area Report and SAR, respectively. Below are the assumptions specific to the proposed Generating Facility:

I. Environmental Activities, Permits, and Licensing.

Table D.3 Environmental Activities & Licensing evaluation per SCE Facilities or Upgrades

SCE Facility or Upgrade Classification	Assumed Licensing (y/n)	Environmental Activities Assumed Roles and Responsibilities	Declaration Required (y/n)
--	-------------------------	---	----------------------------

⁵ The MW output at the POI varies under different operating conditions. The IC is reminded that this value is tied to the generation tie-line (gen-tie) losses. The estimated Maximum Net Output value at POI and gen-tie losses illustrated above are contingent upon the accuracy of the technical data provided by the IC and are subject to change should the IC change its gen-tie parameters during the final engineering and design phase of the Generating Facility. Please note that the Generating Facility shall not exceed the total net output of [REDACTED].



For further details on the environmental evaluation and permitting/licensing requirements for generator interconnection projects, refer to Appendix K of the Area report.

If no “X”, “Y”, or “N” is entered in a specific row of Table D.3, then assume no environmental scope of work or costs would apply to such SCE facilities disclosed in Attachment 1.

- Assumed Licensing:
 - a. If yes is indicated in Table D.3, SCE assumes construction of SCE’s Interconnection Facilities (“IF”) and/or Distribution Upgrades (“DU”) needed to interconnect the Generating Facility will require a California Public Utilities Commission (“CPUC”) license.
 - b. If no is indicated in Table D.3, SCE assumes construction of SCE’s IF and/or DU needed to interconnect the Generating Facility will not require a CPUC license.
 - c. Such assumptions will be reviewed and verified after execution of a GIA when detailed engineering and environmental review occur.

- Environmental Activities Assumed Roles and Responsibilities:
 - i. If “IC/SCE-Shared” is marked in Table D.3:

SCE Scope of Work

1. SCE will act as the lead for regulatory agency communication for permits issued to SCE covering such SCE facilities.
2. If licensing is assumed, SCE will file for an “expedited” Certificate of Public Convenience and Necessity or “expedited” Permit to Construct by attaching the IC’s certified final California Environmental Quality Act (“CEQA”) document with SCE’s scope of work sufficiently incorporated in lieu of a Proponent’s Environmental Assessment (“PEA”). If a CEQA document is not required for the Generating Facility or if the Generating Facility’s CEQA document does not sufficiently incorporate SCE’s scope of work, SCE may be required to prepare a PEA for SCE’s scope of work. In such cases, SCE’s assumed environmental work and licensing level of effort will increase, resulting in the need to update cost and duration estimates, and potentially amend the GIA.
3. SCE environmental activities may include, but are not limited to, the following:
 - a) Perform all environmental studies and construction monitoring of SCE internal substation construction activities and provide study results to the IC for inclusion in its environmental documents, if applicable.

- b) Collaborate with the IC during the environmental study phase on the IC's proposed study methodologies and findings, as studies are being planned and performed for SCE's scope of work.
- c) Review IC's CEQA and/or National Environmental Policy Act ("NEPA") documents, technical studies, surveys, and other environmental documentation to ensure SCE's scope of work is adequately described in such documents (IC will include SCE's scope of work in its environmental documents. If the Generating Facility's CEQA and/or NEPA documents do not sufficiently incorporate SCE's scope of work, SCE's assumed environmental work and permitting level of effort may increase, resulting in the need to update cost and duration estimates, and potentially amend the GIA).
- d) Review SCE's internal existing technical reports/documents when available.
- e) Prepare SCE's project description, including scope changes during permitting/pre-construction or construction.
- f) Communicate scope changes to the IC's environmental team and discuss/approve subsequent actions including new surveys as necessary.
- g) Complete General Order 131-D Consistency Determination and Environmental Evaluation.
- h) Regulatory agency communication, consultation, reporting, and acquisition of SCE permits addressing SCE's facilities and scope of work.
- i) Prepare environmental requirements for construction clearance.
- j) Develop communication plan.
- k) Perform pre-construction coordination field visit.
- l) Provide Environmental Awareness/Worker Environmental Awareness Program ("WEAP") training.
- m) Perform construction monitoring oversight.
- n) Complete construction and post-construction site assessments.

IC Scope of Work

1. IC will perform all environmental studies and prepare draft environmental permit applications related to the installation of such SCE facilities, except for the SCE internal substation activities as described above. The IC's responsibilities include as applicable, but are not limited to: notifications to the Native American Heritage Commission ("NAHC") and follow-up notifications to the tribes and individuals in the NAHC contact list; performing cultural and paleontological resources records searches, cultural resources inventories (survey and recording), testing and evaluation and/or data recovery of archaeological sites, and appropriate documents in the form of inventory reports, research design, and/or data recovery reports; cultural and paleontological monitoring when/if required, and arranging curation agreements for artifacts and fossil specimens collected; performing a California Natural Diversity Database search, habitat assessment, and protocol or focused surveys for species with the potential of occurring in identified suitable habitat; conducting jurisdictional delineations for wetlands and other regulated waters; preparing draft environmental permit applications, pre-construction biological resource surveys for such SCE facilities, biological resource monitoring during construction of such SCE facilities; mitigation costs including, but not limited to, offsite/compensatory mitigation and onsite restoration, and developing mitigation plans or other environmental reports or submittals to support installation of such SCE facilities.

2. Prior to commencing work and during execution of work, the IC should collaborate and obtain SCE concurrence on all work outlined above. Should the IC-performed environmental studies, surveys, or construction monitoring not meet the Federal or State industry standards in accordance with Applicable Laws and Regulations, and as determined by SCE, the IC shall be obligated to remedy deficiencies under SCE's direction.
- ii. If "SCE Only" is marked in Table D.3:
1. SCE will perform all required environmental studies, prepare environmental permit applications, obtain required environmental permits, and perform required monitoring of all SCE construction activities, and undertake habitat mitigation as required, including, but not limited to, offsite/compensatory mitigation and onsite restoration, related to the installation of such SCE facilities.
 2. Under certain circumstances, such SCE facilities may need to be described and analyzed as part of the IC's CEQA and/or NEPA documents for the Generating Facility. Further coordination to discuss these circumstances may occur during GIA negotiations and/or after GIA execution. Any changes to the environmental and licensing assumptions may result in the need to update cost and duration estimates, and potentially amend the GIA.

➤ Declaration Required:

As a requirement for Interconnection Customers' shared responsibility to perform the Environmental Activities for SCE-owned IF and DU as disclosed above, and to ensure proper accounting of costs used in the calculation of the ITCC and Operations & Maintenance ("O&M") charges, referred to as an Interconnection Facilities Charge and/or a Distribution Upgrades Charge, if applicable, in the forthcoming GIA for the Generating Facility, the IC is required to complete and submit an Environmental Services Costs Declaration for SCE-owned IF and/or DU required to interconnect the Generating Facility. An authorized representative of the IC will sign the declaration attesting to the actual costs spent on environmental services work that would otherwise have been performed by SCE for SCE-owned IF and DU (if applicable) required to interconnect the Generating Facility.

The declaration shall be provided to SCE by a specified date in the Generating Facility's forthcoming GIA Appendix B - Milestone table. Should the IC fail to provide the declaration by the specified deadline, SCE will hold the IC in default of the GIA pursuant to the terms therein. The costs stated by the IC in the declaration, once approved, will be used by SCE to adjust the ITCC and the applicable monthly O&M charges for the Generation Facility and will be reflected via an amendment to the GIA upon true-up.

The information stated in the declaration is subject to review and/or audit by SCE pursuant to the terms and conditions in the forthcoming GIA. Should an audit be deemed necessary by SCE, the IC will need to provide supporting documentation (copies of invoices/receipts) to substantiate the costs stated in the declaration within ten (10) business days from receipt of notice.

II. BESS Considerations:

- SCE offers ACDS pursuant to SCE's WDAT Energy Storage filing under Docket No. ER19-2505 accepted by FERC and effective October 30, 2019. Interconnection

customers will be assessed charges for ACDS in accordance with Attachment K to the WDAT.

- The final design and construction of the BESS resource of the Generating Facility will need to comply with SCE’s Interconnection Handbook and conform with SCE’s Distribution Standards and Practices .
- This study assumes that the Generating Facility will include all equipment, software, appropriate controls, and other related equipment necessary to maintain Charging Capacity restrictions per SCE’s requirements.
- The preliminary charging analysis discussed in this report assumed that the requested Charging Capacity is curtailable before wholesale and retail load, and this assumption was used to determine the charging restrictions mentioned in this report for the Generating Facility.
- The BESS resource of the Generating Facility will need to be metered separately. The IC may be required to install multiple sets of metering (i.e. separate sets of potential transformers & current transformers and supporting metering equipment) for the Generating Facility. Additionally, the Generating Facility may also need to connect the BESS resource to a dedicated transformer.
- Generation projects with a BESS resource electing to receive ACDS and requesting to interconnect to SCE’s Subtransmission System (which is non-ISO controlled 66 kV and 115 kV facilities) will comply and operate pursuant to a static charging schedule in order for SCE to implement charging restrictions until such time SCE’s Distributed Energy Resource Management System (“DERMS”) is placed in service and operational. The static charging schedule provided to the IC may be updated on an as-needed basis or at a minimum once a year to account for factors such as changes in load, Resources, and Firm Charging Distribution Service, or modifications to the Distribution System.

III. Other Items to Consider:

- [REDACTED]

E. STUDY RESULTS

1. ISO Grid

a. Generation Export Analysis

i. Steady State Power Flow Reliability Analysis

The results of the ISO Grid reliability analysis, which are discussed in detail within the Area Report, indicate that [REDACTED]

[REDACTED]

ii. Transient Analysis

Refer to the Area Report for details pertaining to the transient stability evaluation criteria and assessment results on the Bulk System.

iii. Subsynchronous Interaction Evaluations

For inverter-based generation, a Subsynchronous Control Interaction (“SSCI”) study is required to assess potential sub-synchronous control interactions with series compensated lines on the SCE Transmission System. The power electronic control system of the generator can interact with the sub-synchronous modes of the transmission system and cause SSCI, particularly when they are electrically close to each other. [REDACTED]

However, as previously mentioned in Section E.5 of this report, all inverter-based generators are required by the ISO Transmission Planning Process Business Practice Manual⁶ to submit/provide the final Power System Computer Aided Design (“PSCAD”) model of the Generating Facility. Such requirement will be included in the GIA as a specific milestone required as part of execution.

Please refer to Attachment 1 for additional requirements after the Generating Facility achieves Commercial Operation.

iv. Deliverability Assessment

Section G – Deliverability Assessment Results of this report provides information on any Delivery Network Upgrades (Local or Area) assigned to the Generating Facility, if any.

v. Short Circuit Duty Analysis

1. SCE-owned Facilities

It was determined that the Generating Facility [REDACTED]

[REDACTED] identified in the QC14 Phase II study.

2. SCE’s Ground Grid Duty Concerns

The QC14 Phase II SCD study determined that the Generating Facility [REDACTED]

[REDACTED] of the Generating Facility.

3. SCD Considerations

The ISD and/or COD of the Generating Facility may be impacted by SCD upgrade(s)/mitigation(s), that were triggered in prior cluster studies and are required only when enough generation projects (with executed GIAs in good standing) achieve ISD. The identification of the need for these upgrades assumes that all queued generation projects materialize and are interconnected, but the true need occurs only when enough queued generation achieves ISD. These SCD

⁶ <https://bpmcm.caiso.com/Pages/BPMDetails.aspx?BPM=Transmission%20Planning%20Process>

mitigations will be continuously evaluated as part of subsequent planning studies and the Annual Reassessment⁷ with queued generation projects to properly define the actual trigger of SCD mitigation based on the actual execution of GIA and development of generation facilities toward commercial operation. For previously triggered SCD mitigation(s), if any, that could impact the timelines for Generating Facility Please refer to Area Report which are titled the following:

- a. Upgrades identified through the GIDAP⁸ which are included in an executed generator interconnection agreement, but are not yet in-service
- b. Upgrades identified through the ISO Transmission Planning Process

b. Charging Analysis

The results to the ISO Grid charging analysis [REDACTED]
[REDACTED]
[REDACTED] Refer to the Area Report for details.

2. Non-ISO controlled Subtransmission System (66 kV or 115 kV)

a. Generation Export Analysis

i. Steady State Power Flow Analysis

1. Thermal Overloads

The subtransmission assessment indicates that the Generating Facility [REDACTED]
[REDACTED]
[REDACTED] s.

I. Normal Conditions

- [REDACTED]

II. Single Contingency

- [REDACTED]

Refer to the SAR for additional information.

2. Power Flow Non-Convergence

[REDACTED] with the inclusion of the Generating Facility operating at the required power factor range; refer to the Area Report and/or SAR for additional details.

3. Voltage Performance

⁷ Please refer to Section 7.4 of ISO Tariff Appendix DD Generator Interconnection and Deliverability Allocation Procedures (“GIDAP”) for additional information.

⁸ ISO Tariff Appendix DD Generator Interconnection and Deliverability Allocation Procedures (“GIDAP”)

Power Factor Evaluation
Inverter Module
Generating Facility MW Output at Terminal (MW)
Ambient Temperature for Generator Capability (°C)
Effective Power Factor at Generator Terminal
0.95 PF Requirements (MVARs)
Reactive Power Requirements
Main GSU Xfrm Losses (MVar)
Collector Losses (MVar)
Aux Load Losses (MVar)
Pad-Mount Xfrm Losses (MVar)
Total VAR Requirements (MVar)
Reactive Power Supply
Shunt Capacitors Banks (MVar)
Collector Line Charging (susceptance) (MVar)
Inverter VAR output at Pgen (MVar)
Total VAR Supplies (MVar)
VAR Surplus/ Deficiencies (+/-) (MVARs)
Dynamic VAR Surplus/ Deficiencies (+/-) (MVARs)



Based on the technical details provided, the Generating Facility, as proposed, has

[Redacted]

ii. Transient Analysis

1. Generating Facility Performance

[Redacted]

[Redacted]. During initial synchronization, the IC and SCE will conduct tests on the Generating Facility’s electric generating units as required by Good Utility Practice per the forthcoming GIA. If the actual dynamic performance of the interconnected Generating Facility does not match the performance of the supplied dynamic model used in the interconnection cluster study process, the IC will update the dynamic model and resubmit to SCE, as required within ninety (90) Calendar Days after the successful initial synchronization tests, unless otherwise agreed.

2. System Performance

[Redacted] Refer to the Area Report for additional details pertaining to the transient stability evaluation criteria and assessment results, respectively.

iii. Short Circuit Duty Analysis

1. SCE-owned Facilities

It was determined that the Generating Facility [REDACTED] [REDACTED] [REDACTED] identified in the QC14 Phase II study.

2. SCE's Ground Grid Duty Concerns

The SCD duty studies [REDACTED] [REDACTED] [REDACTED] [REDACTED]

- [REDACTED]

[REDACTED] [REDACTED] [REDACTED]

Refer to Attachment 1 and Attachment 2 for additional scope and costs information related to these upgrades.

3. Short Circuit Duty Considerations

[REDACTED] [REDACTED] [REDACTED] [REDACTED]

b. As-Available Charging Analysis

Steady State Power Flow Analysis

1. Thermal Overloads

The subtransmission assessment study [REDACTED] [REDACTED] [REDACTED] [REDACTED] [REDACTED] are provided in the corresponding SAR. Provided below is a summary of the overloaded facilities under normal and single contingency conditions.

III. Normal Conditions

- [REDACTED]
- [REDACTED] [REDACTED]
- [REDACTED]

IV. Single Contingency

- [REDACTED]
- [REDACTED]
- [REDACTED]
- [REDACTED]

2. [REDACTED]

3. Voltage Performance
[REDACTED] refer to Area Report and/or SAR for additional details.

4. Power Factor Requirement under ACDS operation of the Generating Facility
[REDACTED]

5. System Limitations under ACDS of the Generating Facility
[REDACTED]

6. Implementation of ACDS Restrictions for the Generating Facility

Given that CMS can only handle BESS project interconnections at the low voltage distribution level, BESS projects interconnecting at the subtransmission level do not qualify to be added to CMS and by default will have to rely solely on a static charging schedule for implementation of ACDS charging restrictions, until DERMS become available.

Refer to Attachment 1 and Attachment 2 for scope description and associated cost responsibility for implementing the static charging schedule for the Generating Facility.

7. Energy Charge Rate for ACDS

In accordance with SCE's Energy Storage filing at FERC amending its WDAT, if the IC elects to receive ACDS, the IC, will be responsible for paying an As-Available Energy Charge Rate (\$/kWh) per month, which is based on the metered energy usage of the Generating Facility and associated Service Level. [REDACTED]

Please refer to Attachment K⁹ of the SCE WDAT, for information on the As-Available Energy Charge Rate applicable to the Generating Facility's BESS resource per its designated Service Level.

F. AFFECTED SYSTEMS


Per GIP Section 3.7, SCE will notify the Affected System¹⁰ Operators that are potentially affected by the active projects in QC14 Phase II. Given the radial nature of SCE's non-ISO controlled subtransmission system, the impacts to Affected Systems connected to such system is limited to incremental SCD at the interface point with the Affected System. As part of this study, SCE evaluates the incremental SCD at the interface point with the potential Affected System. Locations where SCD is increased by at least 0.1 kA will be documented in the study results providing the incremental SCD contribution associated with the active projects in QC14 Phase II.

⁹ Link to attachment k: <https://www.sce.com/regulatory/open-access-information?from=/openaccess>

¹⁰ Affected System shall mean an electric system other than the SCE's Distribution System that may be affected by the proposed interconnection. For purposes of this compliance requirement, Affected Systems will consist of neighboring municipalities.

The specific SCD contribution from the Generating Facility to the interface point between SCE and the potentially Affected System is provided in Table F.1 below. Impacts on the Affected Systems with the addition of all QC14 Phase II projects, are provided in the Area Report (Section H.2), and in Attachment 7.

Table F.1: Short-Circuit Duty Evaluation of Neighboring Utilities Impacted by the Generating Facility



G. DELIVERABILITY ASSESSMENT RESULTS

Please refer to Section G of the Eastern Area Report included in the QC14 Phase II report package for the details on the QC14 Phase II Deliverability Assessment.

For scope and cost information of any Network Upgrades assigned to the Generating Facility, please refer to Attachment 1, Attachment 2, and Attachment 3 of this Appendix A report.

H. METERING

The Phase II Study metering scope and cost was based on proxy methodology that would presumably enable SCE to comply with its metering tariff(s).

Please refer to Attachment 1 and Attachment 2 for the metering associated scope and cost.

The IC is advised that it will be required to comply with SCE's Interconnection Handbook and GIP. The IC's Generating Facility's metering configuration will be evaluated post Phase II or post GIA. If post GIA, finalizing the Generating Facility's metering one-line and determining the number of meter sets required to comply with SCE's metering tariff(s) requirements will be performed in parallel with the engineering and design phase of the Generating Facility. The post GIA analysis may result in additional metering scope and cost and may impact the IC's requested ISD and COD. Any change to the Generating Facility's interconnection configuration or technology after the Phase II Study, including the metering configuration, will require the IC to submit an MMA request in accordance with the GIP. If additional metering scope, cost, and duration are identified because of the IC's modification request, an addendum to the Phase II Study will be issued or the GIA will be amended, respectively.

I. INTERCONNECTION FACILITIES, NETWORK UPGRADES, AND DISTRIBUTION UPGRADES

Please see Attachment 1 for SCE's Interconnection Facilities ("IF"), RNU', Delivery Network Upgrades¹¹ (DNU), and Distribution Upgrades ("DU") allocated to the Generating Facility for physical interconnection, to provide for the requested net MW export at the POI taking into consideration the IC's requested Deliverability, and in support of the IC's request for ACDS. Please note that SCE considered current system configuration, approved SCE sponsored projects, and all queued generation in determining scope for IF and/or plan of service but will not "reserve" the identified scope of upgrades for the proposed POI unless a GIA is executed per the specified timelines shown in Table K.1.

J. COST AND DURATION ESTIMATE

I. Cost Estimate


The Generating Facility's estimated interconnection costs, adjusted for inflation and provided in 'constant' 2023 dollars escalated to the Generating Facility's feasible COD (as identified below in Table K.1), are provided in Attachment 2 and the Generating Facility's allocated cost for shared network upgrades are provided in Attachment 3 to this Appendix A report. The interconnection costs will be documented in the forthcoming GIA for the Generating Facility. However, should there be a delay in executing the GIA beyond 2024 (e.g., the IC decides to "park" the Generating Facility pursuant to GIP Section 4.6.13), a new cost estimate adjusted for inflation will be required and reflected into the GIA.

II. Preliminary Durations

The estimated duration(s) shown in Table J.1 represents the estimated time needed for SCE to design, engineer, procure, and construct the applicable facilities with the start date of the estimated duration based on the effective date of the GIA; and timely receipt of all required information, written authorization to proceed ("ATP"), project payments, financial security

¹¹ At the IC's discretion, the IC or parties other than SCE pursuant to Section 10.2 under GIP may construct an Option (B) Generating Facility Area Delivery Network Upgrades (ADNUs) not allocated TP Deliverability. If SCE does not construct the ADNUs, the IC is not required to make the third Interconnection Financial Security posting to SCE pursuant to Section 4.8.4.2.1 under GIP.

postings, and timely completion of project milestones. The estimated durations for the facilities identified for the Generating Facility are as follows:



Notes:

¹² **Short Circuit Duty Mitigation Durations:** It is important to note that short-circuit duty upgrades identified as part of the QC14 Phase II interconnection studies were derived with the inclusion of all active higher-queued generation projects without regard to corresponding desired in-service dates or actual project status. Changes to the higher-queued generation projects as well as changes to generation projects in QC14, such as withdrawals, downsizing, suspensions, or deferrals to proposed in-service dates, may allow for the identified earliest in-service to be accelerated to align with the construction timing for the plan of service and Interconnection Facilities needed to interconnect the project. Ultimately, SCD upgrades will be scheduled based on actual development of generation resources identified to meaningfully increase SCD on the identified overstressed circuit breakers as determined based on execution of Generation Interconnection Agreements or other agreements that commit a project towards development.

1. **Duration Estimates and Identified Upgrades**

Durations identified in this section may vary. During the cluster study process, SCE includes all queued and active generation projects without regard to corresponding desired in-service dates or actual status to identify system upgrades, including SCD related upgrades, and a duration for SCE to build them. Such duration affects the ISD for this specific Generating Facility. As status for queued projects change (withdrawals, downsizing, suspensions, or deferred in-service dates), SCE may be able to accelerate in-service dates for projects affected by status changes. Furthermore, SCE will only begin design/construction of an identified system upgrade when enough projects 1) execute and fund a GIA and/or a Letter Agreement with SCE and 2) those projects trigger the need for an upgrade.

2. **Coordination of Environmental Work**


This study assumes that the IC will perform environmental work related to the installation of SCE’s IF, and DU as specified in this report. The IC is advised that any durations provided above assume that the IC will perform this environmental work in parallel with SCE’s preliminary design and engineering. The IC is expected to engage SCE to obtain concurrence prior to commencement of any environmental work and during execution of that work. Since SCE will be using the IC’s environmental documents and/or work products, an IC delay in producing them may impact SCE’s ability to obtain required permits and/or license(s) in time to target the IC’s requested ISD. Such delays would likely cause additional delays in the commencement of SCE’s final design and engineering, procurement, and construction. These delays could increase any durations identified in this report and as stated above, could impact the ISD provided in Table K.1 ISD and COD Assessment.

[REDACTED]

3. **Circuit Breaker Procurement Delays**

Due to supply chain issues, the lead times associated with procuring equipment, particularly Circuit Breakers (CB), have increased across the industry. Specifically, this procurement challenge impacts the estimated duration to physically interconnect a generating facility, and any short circuit duty mitigation that requires replacing CBs. Consequently, estimated durations for these types of upgrades have increased and are reflected in this report under their applicable upgrade classification (generally as either a Reliability Network Upgrade, a Distribution Upgrade and/or Interconnection Facility associated with the Plan of Service). The estimated durations for CBs in this report are based on vendor information known to date and are subject to change.

4. [REDACTED]



K. IN-SERVICE DATE AND COMMERCIAL OPERATION DATE ASSESSMENT


An ISD and COD assessment was performed for the Generating Facility to establish SCE’s estimate of the earliest achievable ISD based on the cluster study process timelines and the time required for SCE to complete the facilities needed to enable physical interconnection as an Interim Deliverability Status or Energy-Only Deliverability Status interconnection (as applicable) for the Generating Facility. This date may be different from the IC’s requested ISD and will be the basis for establishing the associated milestones in the draft GIA.

1. ISD Estimation Details

For the QC14 Phase II Interconnection Study, the estimated earliest achievable ISD is derived by the time requirements to complete the following:

1. QC14 Interconnection Study Cycle
2. Tender a draft GIA
3. Negotiate and execute the GIA
4. Longest duration associated with the facilities required to interconnect the Generating Facility (i.e., IF, RNU, and DU), per the durations specified in table J.1. above.


Table K.1 ISD and COD Assessment



Notes on the Achievable ISD and COD calculation:

- 1) This calculation assumes the estimated duration to construct those facilities required for the Generating Facility to achieve Interim Deliverability Status or Energy-Only Deliverability Status (as defined in the ISO Tariff) until the applicable DNU's are completed.
- 2) The project execution durations shown represents the estimated amount of time from the effective date of the GIA needed to engineer, design, procure, and construct the facilities that were identified to be triggered in this study; and timely receipt of the IC's initial specification information, written authorization to proceed ("ATP"), project payments, financial security postings, and timely completion of project milestones.
- 3) The IC-requested dates are specified in the IR and/or Attachment B submitted to SCE in accordance with GIP Section 4.6.1. Table K.1 provides SCE's estimated achievable ISD and COD for the Generating Facility in compliance with GIP Section 4.9.2. The actual ISD, Initial Synchronization Date, and COD will depend on licensing, engineering, detailed design, procurement, and construction requirements to interconnect the Generating Facility after the GIA has been executed or filed at the Federal Energy Regulatory Commission ("FERC") for acceptance.
- 4) Assumes that GIA is tendered after the TP Deliverability allocation results are disclosed, the required affidavit is submitted accepting or rejecting the deliverability allocation, and the IC has submitted written notification to SCE requesting a draft GIA.

2. ISD Conclusion



L. TIMING OF FULL CAPACITY DELIVERABILITY STATUS, INTERIM DELIVERABILITY STATUS, AREA CONSTRAINTS, AND OPERATIONAL INFORMATION

The Generating Facility would be granted its requested FCDS only if the Generating Facility receives a Transmission Plan Deliverability (“TPD”) allocation in the forthcoming TPD Allocation Study Process. Furthermore, timing of obtaining the requested FCDS is dependent on the completion of assigned Delivery Network Upgrades (“DNU”) and Precursor Network Upgrades (“PNU”) ¹³ identified in the QC14 Phase II Transmission Deliverability Analysis. The identified DNU’s and PNU’s if any, may be updated in any subsequent annual reassessment. Until such time that these DNUs and PNUs are completed and placed in-service, the Generating Facility may be granted Interim Deliverability Status based on annual system availability. For a discussion on the deliverability study results and the potential timing of FCDS once a TPD allocation has been obtained, refer to Section E of the Area Report.

¹³ PNUs are Network Upgrades required for an Interconnection Customer that consist of (1) Network Upgrades whose cost responsibility is assigned to an earlier Interconnection Customer that has executed its GIA; and (2) Network Upgrades in the approved ISO Transmission Plan.

Attachment 1:
Interconnection Facilities, Network Upgrades, and Distribution Upgrades
Please refer to separate document

Attachment 2:
Escalated Cost and Time to Construct for Interconnection Facilities, Reliability Network Upgrades,
Delivery Network Upgrades, and Distribution Upgrades
Please refer to separate document

Attachment 3:
**Allocation of Network Upgrades for Cost Estimates and Maximum Network
Upgrade Cost Responsibility**
Please refer to separate document

Attachment 4:

SCE's Interconnection Handbook

Preliminary Protection Requirements for Interconnection Facilities are outlined in SCE's Interconnection Handbook at the following link:

<https://on.sce.com/InterconnectionHandbook>.

Attachment 5:
Short-Circuit Duty Calculation Study Results
Please refer to the Appendix H of the Area Report

**Attachment 6:
IC Provided Generating Facility Dynamic Data**

[REDACTED]

Attachment 7:
Subtransmission Assessment Report (SAR)
Please refer to separate document